

Celadon Inc.
RCV-5000 IR to RS-232 Output Table
Device: Canon Projector LV-7345/LV7355

Infrared Remote Control: Philips PRONTO, Niles Intellicontrol
 Infrared Code Format: NEC - Device ID: 7B02
 Infrared Pronto Data File(s): See "IR Code Read Me - RCV-5000.txt" for complete description
 Infrared Receiver: Celadon RCV-5000 Infrared to RS-232 Receiver
 RCV-5000 Data File: canon1_r.hex
 Note: Carriage return at end of string.
 Data: 19200 Baud, 8, N, 1, ASCII Output
 Standard Transmit and Receive pinout
 **Mini 8 pin Connector - customer will need to re-wire DB-9 to MiniDin

Canon Function	Pronto Button	RCV-5000 Output
Power On	0	C00
Compulsion Power Off	1	C01
Power Off	2	C02
Computer Analog Mode	3	C05
Video Mode	4	C06
MCI Mode	5	C07
Computer Digital Mode	6	C08
Volume +	7	C09
Volume -	8	C0A
Audio Mute ON	9	C0B
Audio Mute OFF	10	C0C
No Show ON	11	C0D
No Show OFF	12	C0E
Regular Video Image (4:3)	13	C0F
Wide Video Image (16:9)	14	C10

Celadon, Inc.
 50 Mitchell Blvd.
 San Rafael, CA 94903
 Sales: (707) 648-1098
 Main Tel: (415) 472-1177
 Main Fax: (415) 472-1179
 sales@celadon.com